

S E R V I C E N O T E

SUPERSEDES: None

J2208B Protocol Analyzer (4959A Pod)

Serial Numbers: 0000A00000 / 3324A00380

Exceptions (Serial Numbers already modified):

3212A00104, 3212A00127, 3212A00134, 3212A00140, 3212A00161, 3212A00228,
 3212A00230, 3212A00250, 3212A00267, 3212A00268, 3212A00269, 3212A00282,
 3212A00310, 3212A00314, 3212A00315, 3212A00316, 3212A00317, 3212A00337,
 3212A00340, 3212A00341, 3212A00342, 3212A00346, 3212A00360, 3212A00366,
 3212A00367, 3212A00369

**Revised J2208B Main board/A1 Assembly will work with T1/E1
 (1.544/2.048Mbps) speed analysis. Older boards (J2208-66502/3/5/6)
 are not compatible.**

Parts Required:

Part No.	Qty.	Description
5063-1876	1	J2208B Main Board
5063-1875	1	J2208B Katakana Main Board

Continued

DATE: 24 September 1993

ADMINISTRATIVE INFORMATION

SERVICE NOTE CLASSIFICATION:			
MODIFICATION RECOMMENDED			
ACTION CATEGORY:	<input type="checkbox"/> IMMEDIATELY <input type="checkbox"/> ON SPECIFIED FAILURE <input checked="" type="checkbox"/> AGREEABLE TIME	STANDARDS:	Labor 1.0 hrs
LOCATION CATEGORY:	<input type="checkbox"/> CUSTOMER INSTALLABLE <input type="checkbox"/> ON-SITE <input checked="" type="checkbox"/> SERVICE CENTER	SERVICE INVENTORY:	<input type="checkbox"/> RETURN <input type="checkbox"/> SCRAP <input checked="" type="checkbox"/> SEE TEXT
AVAILABILITY:	PRODUCT'S SUPPORT LIFE	USED PARTS:	<input type="checkbox"/> RETURN <input type="checkbox"/> SCRAP <input checked="" type="checkbox"/> SEE TEXT
AUTHOR: NB	ENTITY: 3800	AGILENT RESPONSIBLE UNTIL: September 1994	
		ADDITIONAL INFORMATION:	

Situation:

The older pod boards J2208-66502/3/5/6 are not compatible with the T1/E1 assemblies.



CAUTION

Take static precautions during modification.

Solution/Action:

Perform the following modification:

1. Remove pizza box from 4959A
2. Remove cover, locate J2208-66502/3/5/6 board assy and remove.
3. Install new board assembly 5063-1875 or 5063-1876.
4. Check J2113A mainframe, if serial number is "A00163", perform service note J2213A-02.
5. Reinstall top cover.
6. Reboot and access 4959 HPTOOLS.
7. Perform J2208B self test.