

S E R V I C E N O T E

SUPERSEDES: None

66104A System DC Power Supply

Serial Numbers: 3207A00101 / 3207A00369

Supply oscillates at 3KHz**To Be Performed By:** Agilent-Qualified Personnel**Parts Required:**

Part No.	Description
0160-4831	Capacitor, 4700pF
0757-0349	Resistor, 22.6k 1%

Situation:

The supply output oscillates at 2 to 3 KHz in the range of 2 to 5 volts at currents above 1.5 amps and an AC input line voltage below 210 VAC.

Continued

DATE: 26 January 1993

ADMINISTRATIVE INFORMATION

SERVICE NOTE CLASSIFICATION:			
MODIFICATION RECOMMENDED			
ACTION CATEGORY:	<input type="checkbox"/> IMMEDIATELY <input checked="" type="checkbox"/> ON SPECIFIED FAILURE <input type="checkbox"/> AGREEABLE TIME	STANDARDS:	Labor 0.5 Hours
LOCATION CATEGORY:	<input type="checkbox"/> CUSTOMER INSTALLABLE <input type="checkbox"/> ON-SITE <input checked="" type="checkbox"/> SERVICE CENTER	SERVICE INVENTORY:	<input type="checkbox"/> RETURN <input type="checkbox"/> SCRAP <input type="checkbox"/> SEE TEXT
		USED PARTS:	<input type="checkbox"/> RETURN <input checked="" type="checkbox"/> SCRAP <input type="checkbox"/> SEE TEXT
AVAILABILITY:	PRODUCT'S SUPPORT LIFE	AGILENT RESPONSIBLE UNTIL: 26 January 1995	
AUTHOR: DF	ENTITY: 2100	ADDITIONAL INFORMATION:	

Solution/Action:

Change C311 to 4700pF and R311 to 22.6K ohms.

The following serial numbers have already been modified:

3207A-00193, 00306, 00307, 00321, 00334, 00336, 00337, 00338,
00339, 00342, 00344, 00345, 00347, 00348, 00350, 00351,
00358, 00360, 00361, 00362, 00364, 00366, 00367, 00368