

S E R V I C E N O T E

SUPERSEDES: NONE

E3617A Lab Bench DC Power Supply

Serial Numbers: KR51301277 / KR61301519

To eliminate possible open circuit in the pattern trace of the printed circuit.

Duplicate Service Notes: E3616A-02

Parts Required: 20 AWG (40 mm length)

To be performed by: Agilent-Qualified Personnel

Situation:

No output in the output terminals of the power supply due to the open circuit connection caused by improper pad design between C8 and PCB pattern trace or C7 and PCB pattern trace.

Solution/Action:

1. Connect a jumper wire between (+) terminal of C8 and (+) terminal of C7.
2. Connect a jumper wire between (-) terminal of C8 and (-) terminal of C7.

DATE: January 1997

ADMINISTRATIVE INFORMATION

SERVICE NOTE CLASSIFICATION:					
MODIFICATION RECOMMENDED					
ACTION CATEGORY:	<input type="checkbox"/> IMMEDIATELY <input checked="" type="checkbox"/> ON SPECIFIED FAILURE <input type="checkbox"/> AGREEABLE TIME	STANDARDS:	LABOR 1.0 Hours		
LOCATION CATEGORY:	<input type="checkbox"/> CUSTOMER INSTALLABLE <input type="checkbox"/> ON-SITE <input checked="" type="checkbox"/> SERVICE CENTER	SERVICE INVENTORY:	<input type="checkbox"/> RETURN <input type="checkbox"/> SCRAP <input checked="" type="checkbox"/> SEE TEXT	USED PARTS:	<input type="checkbox"/> RETURN <input type="checkbox"/> SCRAP <input checked="" type="checkbox"/> SEE TEXT
AVAILABILITY:	PRODUCT'S SUPPORT LIFE		AGILENT RESPONSIBLE UNTIL: January 1999		
AUTHOR: NKP	ENTITY: Y300	ADDITIONAL INFORMATION:			