4395A-14A

# SERVICE NOTE

Supersedes: 4395A-14

# Agilent 4395A Network/Spectrum/Impedance Analyzer

**Serial Numbers: See Solution / Action** 

**Part Number Changes for Power Supply Switch Parts** 

To Be Performed By: Agilent-Qualified Personnel

Parts Required: See Solution / Action

## ADMINISTRATIVE INFORMATION

SERVICE NOTE CLASSIFICATION:

# **INFORMATION ONLY**

AUTHOR: jm PRODUCT LINE: WN

ADDITIONAL INFORMATION:

© AGILENT TECHNOLOGIES, INC. 2006 PRINTED IN U.S.A.



July 26, 2006

Page 2 of 4 4395A-14A

#### **Situation:**

The power switch holder (P/N 04396-01274) and the power switch assembly (P/N 04396-61701) for the 4395A were obsoleted and replaced with new parts. Additionally, a new rod (P/N 04194-40001), which is inserted between the switch and LINE push-button, is set up.

### **Solution/Action:**

When replacing the switch holder or the switch assembly, order appropriate parts depending on the serial number of the 4395A.

### Serial Number: JP1KE02221 and below

When either the switch holder (P/N 04396-01274) or the switch assembly (P/N 04396-61701) is faulty, replace all the parts listed in Table 1 with the new parts shown in Table 2. Insert the rod (P/N 04194-40001) between the power switch and LINE push-button as shown in Figure 3.

#### Serial Number: JP1KE02222 and above

New switch holder and switch assembly are used in the 4395A. When replacing the switch assembly, holder or rod, use the replacement parts listed in Table 2.

Table 1 Old Parts (Obsoleted)

Part Number	Qty.	Description
04396-01274	1	Switch Holder
04396-61701	1	Switch Assembly
0515-1718	2	Screw fixing 04396-01274 on the chassis
0515-0999	2	Screw fixing Switch Assembly to Switch Holder

Table 2 New Replacement Parts

Part Number	Qty.	Description	Refer
04396-01276	1	Switch Holder	Figure 1 & 3
04396-61702	1	Switch Assembly	Figure 1 & 3
04194-40001	1	Rod for 04396-61702	Figure 2 & 3
5041-0564	1	Gate End	Figure 2
0515-1719	2	Screw fixing 04396-01276 on the chassis	Figure 3
0515-0914	2	Screw fixing Switch Assembly to Switch Holder	Figure 1

Figure 1 Attach Switch Assembly to Switch Holder






Figure 2 Assemble Key Rod Assembly



Page 4 of 4 4395A-14A

Figure 3 Install Switch Assembly and Key Rod



End of Document